

## DCS1800 / WiFi Combiner

**Model : PW-DUP-8013**

1、 Part Number : PW-DUP-8013

2、 Name : Dual-band Combiner

	CH1	CH2
Freq. Range(MHz)	1710~1880	2400~2500
Band-width(MHz)	170	100
Insertion Loss(dB)	≤0.6	≤0.6
Ripple(dB)	≤0.4	≤0.4
Rejection(dB)	≥60@CH2	≥80@CH1
Isolation(dB)	≥60@CH2	≥80@CH1
Return Loss(dB)	≥19	
Impedance(Ω)	50	
PIM(dBc)	≤-140@+43dBm×2	
Connector	N-F	
Power(W)	100	
Temp.(□)	-25~+65	
Dimension(mm)	320×42×28	
Weight(kg)	0.68	

2、 Dimension :

